

**DMSS** is the latest Sapphire mobile app for the DVR/NVR/IP Camera. It is using the P2P technology, simply scanning QR code will allow you easy access from remote.

You can find this App and download it from Google Play or Apple Store. Select Region first. Next, it will display a quick tutorial. Swipe tool bar can display for more options.

After a quick walk thru, then you will see the Main Menu screen. Tap upper-right corner (+) to add the first device.

Tap SN/SN to scan the QR code.

The QR code, you will find from the local DVR monitor or the browser in upper-right corner.

Select the right side QR code, is the SN number.

The left side QR code is for the older mobile app link. You can simply ignore that.

Ater scanned, it will display your Device SN.

Then, you should see the detail adding Information.

Please Enter the device name 0 (aka Nickname) & the device password 2. Tap Save 8 to finish it.

10



Select the device category. For example, NVR.

After wait a little be, It will start to connect. Congratulation, you should be able to see the device video from the remote.



<sup>© 2018</sup> LT Security, Inc. All Rights Reserved. White papers, data sheets, quick start guides, and/or user manuals are for reference only and may or may not be entirely up to date or accurate based upon the version or models. Product names mentioned herein may be the unregistered and/or registered trademarks of their respective owners. The knowledge base document designs for the internal training purpose only.



## **Enable Push Notification in Mobile App**

This section only demonstrates the simple setup and how to enable the Push notification.

	system	
	GENERAL	Firewall System Service
PLAYBACK AI AI ALANY - ALANY - ALANY - ANALY -		Mobile Phone Push
OPERATION BACKUP DISPLAY		
Configuration of the second se		
		Private Protocol Au Security Mode (Reco *
📷 CAMERA 🚯 NETWORK 🚔 STORAGE 🎲 SYSTEM 🔪 💄 ACCOUNT		
		Apply Cancel

The Mobile Push Notification is already enabled by default from the DVR/NVR.

- 1. Go to (...) > Device Details.
- 2. Notification
- 3. Switch On on the top ① Tap Motion Detect ②
- 4. In the Motion Detection section, SMD function requires (Smart Motion Detection) camera. **Tap** Motion Detection (for example)
- 5. Select the Camera you want to be notified of.
- Click < on the left to go back. It will display how many channels has been enabled.
- 7. Tap **Save** to finish enable the push notification. That's it.

88	1	Home	Q	$\oplus$	<	4ch NVR		(	Ach NVR	Save	
								-			
<b>3</b>	Rissback	Boor	Eavoritas		Device Co	nfiguration	4ch NVR >	4ch NVR			
	riajoace	2001	(Terentes	$\cap$	Notificatio	n	>	Motion Detect		2	
CHINVR			PALL	Υ	Stream Se	tting	>	Cam Masking		>	
		F.		1.1	Remote Co	onfiguration	38	Defocus		2	
			6	+	Alarm Out	put	2	Face Alarm		>	
ACH NVR				-	Other Parameters >			License Plate Recognition			
Device	Detans			-				Al Analysis		>	
Move to	the top			_				Stereo Vision		5	
								Thermal Alarm	1	>	
		0	6					Audio Alarm		2	
Home Message Me				<u></u>	l	Delete		Disk Alarm >			
<	Mo	tion Detec	rt		<	Motion Detection	Cancel All	<	4ch NVR	Save	
SMD					IPC		0	4ch NVR		0	
Motion Detection			CAM 2		0	Motion Detect		4 >			
					CAM 3		0	Cam Masking		5	
					CAM 4		0	Defocus		2	
							U	Face Alarm		3	
								License Plate	Recognition	3	
								Al Analysis		5	
								Stereo Vision		3	
								Thermal Alarm		>	
								Audio Alarm			

## When Push Notification Triggered



When the Push Notification has been triggered, your phone will notify <u>a blue icon</u> in the status bar.

Inside the DMSS app message icon will display Red Dot. Tap the Message, then you should be able to see what is happening.

